

It is suggested to keep your projector running with up-to-date benefits from features, applications, and bug improvement. For more details about firmware upgrade instruction and improvements, please read through the following:

Details and Feature Improvements with V1.0.5 & V3.0.5

- New add feature to power on projector with projector remote even without AC power adapter
- Typo correction

Before Firmware Update

Please follow the steps below to make sure that the firmware is for the exact model that you own.

Step 1

Check the "P/N" on projection base.



Step 2

If the P/N of your projector is 9H.JR377.59P, please use the system firmware v3._._. Otherwise, please use the system firmware v1._._ if the P/N of your projector is not 9H.JR377.59P.

How to Update Device Firmware

1. Prepare a USB flash driver and format the USB to FAT32.
2. Download the new firmware from the BenQ website (Support-> Software & Driver -> Firmware) and save it to your USB.
3. Make sure to plug in the AC power for a stable power supply. (DO NOT remove AC power while upgrading)
4. Plug the USB into the projector's Type-A port.
5. Press the "Projector Menu" button on the remote control.
6. Select "System" -> "System Upgrade" -> "USB Update".
7. System will restart once the firmware upgrade is completed.

You're welcome to visit the link below and follow the instruction to update device firmware for more information. <https://youtu.be/ON4oAwaGhCM>

Please feel free to contact BenQ service center in your area if there's anything else above not clear, or have issues about firmware update.

--- Document Ends ---